

4-port Next Generation PerforMax™ sector antenna, 4x 698–896, 65° HPBW, 1x RET and 1x SBT

- Antenna optimized for higher gain with superior radiation efficiency
- Powered by Andrew's SEED® technology (Sustainable Energy Efficient Design)
- Superior patterns for enhanced interference mitigation resulting in improved SINR, higher throughput, and more capacity
- Best in class PIM immunity
- Internal SBTs allow remote RET control from the radio over the RF jumper cable

#### General Specifications

Antenna Type Sector with internal RET and bias tee

**Band** Single band

Color Light Gray (RAL 7035)

**Grounding Type**RF connector inner conductor and body grounded to reflector and mounting

bracket

Performance Note Outdoor usage

Radome Material Fiberglass, UV resistant

Radiator MaterialAluminumReflector MaterialAluminumRF Connector Interface4.3-10 Female

**RF Connector Location**Bottom

RF Connector Quantity, low band 4
RF Connector Quantity, total 4

#### Remote Electrical Tilt (RET) Information

**RET Hardware** CommRET v2

**RET Interface** 8-pin DIN Female | 8-pin DIN Male

**RET Interface, quantity** 1 female | 1 male

Input Voltage 10-30 Vdc
Internal Bias Tee Port 1

Internal RET Low band (1)

Power Consumption, active state, maximum 10 W Power Consumption, idle state, maximum 2 W

ANDREW®
an Amphenol company

Protocol 3GPP/AISG 2.0

**Dimensions** 


 Width
 640 mm | 25.197 in

 Depth
 235 mm | 9.252 in

 Length
 1499 mm | 59.016 in

Net Weight, antenna only 35 kg | 77.162 lb

### Array Layout



Array ID	Frequency (MHz)	RF Connector	RET (SRET)		SBT RF PORT	SBT No.	RET UID
R1	698-896	1 - 2	- 1	1 AISG1	1	1	CPxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx
R2	698-896	3 - 4					

(Sizes of colored boxes are not true depictions of array sizes)

### Port Configuration



### **Electrical Specifications**

**Impedance** 50 ohm

**Operating Frequency Band** 698 – 896 MHz

Polarization ±45°

**Total Input Power, maximum** 600 W @ 50 °C



### **Electrical Specifications**

	R1,R2	R1,R2
Frequency Band, MHz	698-806	806-896
RF Port	1-4	1-4
Gain, dBi	14.9	15.1
Beamwidth, Horizontal, degrees	65	62
Beamwidth, Vertical, degrees	14.3	12.9
Beam Tilt, degrees	2-16	2-16
USLS (First Lobe), dB	15	15
Front-to-Back Ratio at 180°, dB	30	29
CPR at Boresight, dB	18	18
Isolation, Cross Polarization, dB	25	25
Isolation, Inter-band, dB	25	25
VSWR   Return loss, dB	1.5   14.0	1.5   14.0
PIM, 3rd Order, 2 x 20 W, dBc	-153	-153
Input Power per Port at 50°C, maximum, watts	300	300

### Mechanical Specifications

Wind Loading @ Velocity, frontal	579.0 N @ 150 km/h (130.2 lbf @ 150 km/h)
Wind Loading @ Velocity, lateral	162.0 N @ 150 km/h (36.4 lbf @ 150 km/h)
Wind Loading @ Velocity, maximum	739.0 N @ 150 km/h (166.1 lbf @ 150 km/h)
Wind Loading @ Velocity, rear	361.0 N @ 150 km/h (81.2 lbf @ 150 km/h)
Wind Speed, maximum	241 km/h (150 mph)

### Packaging and Weights

Width, packed	752 mm   29.606 in
Depth, packed	387 mm   15.236 in
Length, packed	1654 mm   65.118 in
Weight, gross	50.5 kg   111.333 lb

### Regulatory Compliance/Certifications

Agency	Classification	
UK-ROHS	Compliant	

#### Included Products



Page 3 of 4

BSAMNT-3

Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members.
 Kit contains one scissor top bracket set and one bottom bracket set.

### \* Footnotes

**Performance Note** Severe environmental conditions may degrade optimum performance